

TorchLyte™ Plus is a wireless Master/Satellite system controlled with IR remote or mobile device APP to select 12 or full spectrum colors and multiple animation effects with extended RF range. The Master/Satellite design gives instant control of unlimited number of Satellite Lamps. TorchLyte™ Plus uses 72 Ultra-bright LEDs. Includes our Patented Flame Effect! One Master is required and unlimited number TorchLyte Satellites can be added.

TorchLyte™ functions are controlled using your Android or IOS mobile device in a direct WiFi connection wireless network. Or with optional Infrared remote control.

Mobile Device APP Remote Control Operation:

- **OFF/On** – Turns on the TorchLyte™, recalls last operating mode and color.
- **Brightness Slider** Adjusts the brightness light level and Flame color.
- **Select A** —Selects the Flame mode.
- **Select B** – Selects Color Wheel. Adjust Wheel to any color or hue including white and greys.
- **Select C** - Rotates through the full-spectrum color pallet over a 10 minute period.
- **Select D** - Special Effects patterns, press **Batt** button to select
- **Batt Button** - With OFF/On to OFF, press Batt button to indicate the battery level.

IR Remote Control Operation:

- **OFF/On** – Turns on the TorchLyte™, recalls last operating mode and color.
- **Brightness Up/Dn** Brightness is controlled with "Sun" icons, with levels Up and Down. ☀
- **Candle** —Selects the Flame mode. Slider can adjust the Flame Color. (power on default)
- **Light** – Selects bright white color.
- **Smooth** - Rotates through the color pallet over a 10 minute period.
- **Flash** - Special Effects patterns, press **On** button to select 5 additional patterns.
- **Batt Check** - In Smooth mode, press **On** button to indicate the battery level.
- **Timer** Timer will turn off lamp after 4/8/12 hours, cancel by pressing "Off" Press Timer button once for 4hrs. Lower LED Green. Twice for 8 hrs. Mid LED Blue. Third for 12 hrs. High LED purple.
- **Color** buttons - Selects any of 12 pallet colors.

To check battery level with IR Remote, select "Smooth" mode, then press "On" button to display level. For Phone App, with On/Off switch in "Off" mode, press "Batt" button. (Do NOT hold "On" or "Batt" more than 4 Sec.)

Lamps will automatically turn off when battery is too low and pulsing Red in center of lamp. Recharge immediately to maintain batteries useful life.
When not using lamps or charging, turn off power switch.



Installing TorchLyte APP



Download "RemoteXY Free" App to your device. To operate go to your phone settings, select connections and WiFi. With TorchLyte powered look for "TorchLyteXXX" network and connect using password "moodlyte". Open RemoteXY App then select + to add device network. Select "WiFi Point" connection and look for TorchLyteXXX or <unknown network> and select. You may re-label the Icon by press and hold the icon button.

Pairing with Satellite Lamps

APP - With Master and all Satellites powered on, Press and hold **Batt** button for 5sec. till center Leds show Red.

IR Remote - With Master and all Satellites powered on, Press and Hold **On** button, for 5sec. till center Leds show Red.

Charging Instructions:

1. The Charger Post can be plugged into the smart charger continuously during use or not.
2. TorchLyte™ should be "Off" when charging.
3. Charge time is approximately 3 hours.
4. Turn "Off" TorchLyte™ power switch when not being used longer than 3 days.

Important: Failure to follow these instructions will void the manufacturer's warranty.

1. TorchLyte™ must be fully charged before use.
2. Only use Charger provided with the system. Using another power supply will permanently damage the battery.
3. When Red LEDs's slow blink, Low Battery indicator the TorchLyte™ must be fully recharged.
4. The TorchLyte™ can remain on charger continually when is use or not, trickle charging will extend the batteries useful life.
5. Store the TorchLyte™ System in a cool dry area.
6. Do not submerge or place the TorchLyte charging post into water. The lamp is only water resistant.